

COMMERCIAL RADIO FM TRANSCEIVER

50 GROUP OF CTCSS

214 CODES OF DCS

HIGH/LOW POWER SWITCHABLE

PC PROGRAMMABLE FREQUENCY

AUTO POWER OFF

ROGER BEEP SOUND (ROG)

S-METER BAR

VOX SYSTEM

FREQUENCY DISPLAY MODE

CHANNEL DISPLAY MODE

MEMORY DISPLAY MODE

SET UP NAME PEPLACE CHANNEL

SCAN SYSTEM

DUPLEX FUNCTION

TIME-OUT TIMER

LOW BATTERY ICON ALERT

SELECT WIDE/NARROW-BAND BY KEYPAD

VERSION II

VIBRATION CALLING SYSTEM

ETC.



DHS 8000H **5 watts**
FREQ.136-174.0000MHZ.

FM RADIO BUILT IN

ประหยัดงบประมาณ

วิทยุสื่อสารมาตรฐาน ISO 9001:2000

สำหรับหน่วยงานราชการ / รัฐวิสาหกิจและเอกชน



รับประกันคุณภาพ
อะไหล่แท้และบริการ

- ผลิตเพิลินกับเสียงเพลง FM 87.5-108 MHz.
พร้อม 9 ช่อง Memory สถานีเพลงที่ชื่นชอบ
- DIGITAL CODES & BATTERY Li-ION.



SPENDER®

THE PERFECT TWO WAY RADIOS



ISO 9001:2000
Certificate

Number.FS 517494
องค์กรหนึ่งของคุณไทย

ที่ได้รับมาตรฐานคุณภาพสินค้าและบริการด้านวิทยุสื่อสาร

SPECIFICATION DHS 8000H

General

Frequency cover range	136.0000-174.0000 MHz.
Mode Type	FM (F3E)
Frequency Stability	+/-5 ppm (-20°C to + 55°C)
Operating temperature range	-20°C to +55°C
Power supply requirement	7.4 V DC.
Current Stand-by	40 mA.
Current transmitting	1200 mA.
Antenna impedance	50 Ohm.
Dimensions	90x51x28 mm. (h x w x d)
Weight With battery	185 g.
Step frequency	5.0/6.25/10/12.5/25.0 KHz./By P.C.
Channel Spacing	25.0 KHz / 12.5 KHz.

Transmitter

Power output	Hi : 5 W. Lo : 1 W.
Transmitting current drain	Hi<1.5A / Lo < 870 mA.
Transmitting Frequency error	+/-400Hz
Spurious radiation	-75dBm.
Adjacent channel power	≤ -73 dBm.
Max. frequency deviation	± 5.0 KHz/± 2.5 KHz
Tx distortion	≤ 5 %
Tx frequency response	+1dB to - 3dB of + 6dB. Octave with 300~3000 Hz. For 1000Hz. reference PRE/EMP.
Tx Ham & Noise	≥ 50 dB.

Receiver

Sensitivity	≤ 0.158 μV. at 12 dB. / SINAD
Squelch sensitivity	< 0.141 μV.
Selectivity	≤ -75 dBm.
Intermodulation	≤ -73 dBm.
Squrious response rejection	≤ -73 dBm.
Adjacent channel selectivity	≤ -75 dBm.
Frequency Stability	+/-5 ppm
Audio output max	≥ 500 mW.
Rx distortion	<5% at 8 Ohm Speaker
Audio current max	300~3000 Hz.
Rx frequency response	+1dB to - 3dB of + 6dB. Octave with 300~3000 Hz. For 1000Hz. reference DE/EMP.
Rx Ham & Noise	≥ 50 dB.
IMAGE REJECTION	≤ -73 dBm.



อนุสิทธิบัตร

เลขที่ 4326 - อสป/200 - ข

ภาครับสัญญาณวิทยุระบบ AM และหรือ FM
ในเครื่องรับ - ส่งสัญญาณวิทยุ



หมอก . 2217 - 2548

แบบเตอร์ สปนเตอร์

ได้รับมาตรฐานอุตสาหกรรมอย่างเป็นทางการ

Distribution By
ศูนย์ลูกค้าสัมพันธ์



รับประกันคุณภาพ
อะไหล่และบริการ

Helpline on : 0-2392-1500 (AUTO)

If you still have any problems, please contact our Customer Cares.

: Monday- Saturday 8.30 am.-5.30 pm.

: Sunday and Public Holidays : Closed

www.tccom.co.th

Dealer's Stamp

SPENDER